

SPA 8800

60W Amplifier With Sound Source



- 2 microphones input channels
- Microphone priority function
- MP3 Player
- FM Tuner
- USB and SD Card connectors
- Low impedance Outputs (4-8 Ohms) and 35/70/100V
- Self protection circuit
- Rated power 60W

Siera offers reliable and affordable solutions in Electronic Security, CCTV, Access Control, Intercommunication and Professional Audio.

Output power:	60W
Main Supply:	115 / 230 VAC
AC Power consumption:	90W
Distortion:	< 0,1% (1/3 rated power at 1 KHz)
S/N ratio:	MIC 1,2: 66 dB / AUX 1,2: 70 dB
Inputs:	MIC1: 600 Ohms, 2–6mV MIC2: 600 Ohms, 2–6mV AUX 1: 15K Ohms, 350 mV AUX 2: 15K Ohms, 350 mV
Activated Priority:	On MIC 1
FM Tuner:	Incorporated
Connection for MP3 Player:	USB and SD
Frequency response:	80 Hz to 16 KHz (+/- 3dB)
Tone controls:	Bass boost +/- 10dB at 100 Hz Treble boost +/- 10dB at 10 KHz
Dimensions:	280 x 280 x 80 mm
Net weight:	8.2Kg
Gross weight:	9.8Kg