

# SPA 3220

## 4 Zones Mixing Amplifier



- 5 input channels
- 4 Zones selection 100v
- Microphone priority function
- Pre Output connector
- Amplifier Input connector
- Low impedance output
- Self protection circuit
- Rated power: 220W

Siera offers reliable and affordable solutions in Electronic Security, CCTV, Access Control, Intercommunication and Professional Audio.

<b>Output power:</b>	Maximum: 250W Nominal: 220W
<b>AC Power consumption:</b>	300W
<b>Distortion:</b>	<0,1% (1/3 rated power at 1 KHz)
<b>S/N ratio:</b>	MIC 1,2,3 : 66 dB / AUX 1,2 : 70 dB
<b>Output:</b>	AUX out: 600 Ohms 1V ( 0dB)
<b>Inputs:</b>	MIC1: 600 Ohms, 2-4mV MIC2: 600 Ohms, 2-4 mV MIC3: 600 Ohms, 2-4 mV AUX 1: 15K Ohms, 775 mV AUX 2: 15K Ohms, 775 mV
<b>Activated Priority:</b>	On MIC 1
<b>Frequency response:</b>	80 Hz to 16 KHz +/- 3dB
<b>Tone controls:</b>	Bass boost: +/- 10dB at 100 Hz Treble boost: +/- 10dB at 15 KHz
<b>Speaker outputs:</b>	4-16 Ohms, 100V
<b>Mains supply:</b>	220V AC +/-10% 50/60Hz
<b>Net weight:</b>	18 Kg Approx
<b>Gross weight:</b>	19 Kg
<b>Dimensions:</b>	66 (H) x 484 (W) x 410 (D) mm