

SAC 3703 Cleveraccess Fingerprint Reader for Access Control and Time Attendance



- Access Control + Time Attendance
- <1 sec fingerprint recognition speed
- Fingerprint, ID card an Password access
- Built-In Camera
- 3000 Fingerprint
- Antipassback
- Duress Password
- TF Slot Card

SAC 3703 is part of the new generation "CleverAccess" for Time attendance and Access Control, with fingerprint recognition. Designed with the most advanced and fastest fingerprint algorithm, to get the most reliable and accuracy access.

CPU:	32bit CPU
Fingerprint Sensor:	Optical Sensor
USB Port:	Yes
Built-IN Card Reader:	EM 125 khz
LCD:	2.8" LCD
Keyboard:	15 touch keys + Bell Key
Communication Interface:	RS485/ Wi-Fi & TCP/IP (10/100Mbps)
Output Ports:	Wiegand26/34 bit
Relay Outputs:	Lock and Alarm
Input Ports:	Wiegand 26/34 input
Multi-door Control:	Control up to five Doors with Fingerprint Readers
Camera:	Built-In Camera for Snapshot
Door Sensor:	Supported
Exit Button:	Supported
Voice:	Yes
Real Time Clock:	Supported
Operating Voltage:	DC 12V ± 10% (current : below 0.7A)
Humidity:	20% / 80%
Temperature:	-10° C / 60° C
Fingerprint Capacity:	3000
User Log/ Management Log:	200,000/10,000
Identify Mode:	Fingerprint / Card/ Password
Access Control:	Door / Time Zone / Antipassback / Duress Alarm
Time & Attendance:	Attendance Status, Duty On/Off, Overtime, Time Zone
Yes	Yes
Yes	Yes
Alarm Function:	Support Tamper, Long Time Open Door, Illegal Open Door and Duress Password
Power Management:	Auto Power off / Sleep
USB Port/Download (enroll data, log):	Yes
Self Test:	Yes
Attendance Log Search:	Yes
DHCP:	Yes
Fingerprint Engine Version:	V3.0 FAR/ FRR 0.00001/ 0.1 (%)
Speed:	≤1.0 second (until 50000 fingerprints)
Allowable Finger Rotation:	360° (all direction)
Intelligent Adaptation Function:	Supported
FP Recognition Mode:	1:N, 1:1

Included Accessories:

- 1 pcs patchcord
- 1 pcs ID Card
- Cables and Screws

Not Included Accessories:

- 1 SPS1290, 12V – 1A Power Supply
- WiFi Module

